



**Program Directory for
IBM Developer for z Systems
Host Utilities**

V14.1.0

Program Number 5724-T07, 5655-AC5

FMID HAKGE10

for Use with
z/OS V02.01.00 or later

Document Date: September 2017

G113-2864-08

Note

Before using this information and the product it supports, be sure to read the general information under 7.0, "Notices" on page 30.

A form for reader's comments appears at the back of this publication. When you send information to IBM, you grant IBM a nonexclusive right to use or distribute the information in any way it believes appropriate without incurring any obligation to you.

© **Copyright International Business Machines Corporation 2005, 2017.**

Note to U.S. Government Users — Documentation related to restricted rights — Use, duplication or disclosure is subject to restrictions set forth in GSA ADP Schedule Contract with IBM Corp.

Contents

1.0 Introduction	1
1.1 Developer for z Systems Host Utilities Description	2
1.2 Developer for z Systems Host Utilities FMIDs	2
2.0 Program Materials	3
2.1 Basic Machine-Readable Material	3
2.2 Optional Machine-Readable Material	4
2.3 Program Publications	4
2.3.1 Optional Program Publications	5
2.4 Program Source Materials	5
2.5 Publications Useful During Installation	5
3.0 Program Support	6
3.1 Program Services	6
3.2 Preventive Service Planning	6
3.3 Statement of Support Procedures	7
4.0 Program and Service Level Information	8
4.1 Program Level Information	8
4.2 Service Level Information	8
5.0 Installation Requirements and Considerations	9
5.1 Driving System Requirements	9
5.1.1 Machine Requirements	9
5.1.2 Programming Requirements	9
5.2 Target System Requirements	10
5.2.1 Machine Requirements	10
5.2.2 Programming Requirements	10
5.2.2.1 Installation Requisites	10
5.2.2.2 Operational Requisites	11
5.2.2.3 Toleration/Coexistence Requisites	11
5.2.2.4 Incompatibility (Negative) Requisites	11
5.2.3 DASD Storage Requirements	12
5.3 FMIDs Deleted	15
5.4 Special Considerations	15
6.0 Installation Instructions	16
6.1 Installing Developer for z Systems Host Utilities	16
6.1.1 SMP/E Considerations for Installing Developer for z Systems Host Utilities	16
6.1.2 SMP/E Options Subentry Values	16
6.1.3 Overview of the installation steps	17
6.1.4 Allocate file system to hold web download package	17

6.1.5	Upload the web download package to the host	19
6.1.6	Extract and expand the compressed SMPMCS and RELFILES	20
6.1.7	Sample Jobs	21
6.1.8	Create SMP/E environment (optional)	23
6.1.9	Perform SMP/E RECEIVE	23
6.1.10	Allocate SMP/E Target and Distribution Libraries	23
6.1.11	Allocate, create and mount ZFS Files (Optional)	24
6.1.12	Allocate File System Paths	24
6.1.13	Create DDDEF Entries	25
6.1.14	Perform SMP/E APPLY	25
6.1.15	Perform SMP/E ACCEPT	27
6.1.16	Run REPORT CROSSZONE	27
6.1.17	Cleaning Up Obsolete Data Sets, Paths, and DDDEFs	28
6.2	Activating Developer for z Systems Host Utilities	28
6.2.1	File System Execution	28
6.3	Product Customization	28
6.4	Product FMIDs	28
7.0	Notices	30
7.1	Trademarks	30
Reader's Comments		31

Figures

1.	Program File Content	4
2.	Basic Material: Unlicensed	4
3.	Publications Useful During Installation	5
4.	PSP Upgrade and Subset ID	6
5.	Component IDs	7
6.	Driving System Software Requirements	10
7.	Total DASD Space Required by Developer for z Systems Host Utilities	12
8.	Storage Requirements for SMP/E Work Data Sets	13
9.	Storage Requirements for SMP/E Data Sets	13
10.	Storage Requirements for Developer for z Systems Host Utilities Target Libraries	14
11.	Developer for z Systems Host Utilities File System Paths	14
12.	Storage Requirements for Developer for z Systems Host Utilities Distribution Libraries	14
13.	Storage Requirements for Developer for z Systems Host Utilities Web Download Data Sets	15
14.	SMP/E Options Subentry Values	16
15.	User Entered Values	19
16.	Sample Installation Jobs	21

1.0 Introduction

This program directory is intended for system programmers who are responsible for program installation and maintenance. It contains information about the material and procedures associated with the installation of IBM Developer for z Systems Host Utilities. This publication refers to IBM Developer for z Systems Host Utilities as Developer for z Systems Host Utilities.

Developer for z Systems Host Utilities is available as a component of multiple products. Depending on which product you acquired, different functions of Developer for z Systems Host Utilities will be enabled or disabled.

- IBM Developer for z Systems V14.1.0, program number 5724-T07 (web download)
- IBM Developer for z Systems Enterprise Edition V14.1.0, program number 5655-AC5 (Shopz orderable)

The Program Directory contains the following sections:

- 2.0, “Program Materials” on page 3 identifies the basic program materials and documentation for Developer for z Systems Host Utilities.
- 3.0, “Program Support” on page 6 describes the IBM support available for Developer for z Systems Host Utilities.
- 4.0, “Program and Service Level Information” on page 8 lists the APARs (program level) and PTFs (service level) that have been incorporated into Developer for z Systems Host Utilities.
- 5.0, “Installation Requirements and Considerations” on page 9 identifies the resources and considerations that are required for installing and using Developer for z Systems Host Utilities.
- 6.0, “Installation Instructions” on page 16 provides detailed installation instructions for Developer for z Systems Host Utilities. It also describes the procedures for activating the functions of Developer for z Systems Host Utilities, or refers to appropriate publications.

The rest of this section only applies when Developer for z Systems Host Utilities is ordered via Shopz. It does not apply when you downloaded it from the web.

Select this link to go to the next section: 1.1, “Developer for z Systems Host Utilities Description” on page 2

Before installing Developer for z Systems Host Utilities, read the *CBPDO Memo To Users* and the *CBPDO Memo To Users Extension* that are supplied with this program in softcopy format and this program directory; then keep them for future reference. Section 3.2, “Preventive Service Planning” on page 6 tells you how to find any updates to the information and procedures in this program directory.

Developer for z Systems Host Utilities is supplied in a Custom-Built Product Delivery Offering (CBPDO, 5751-CS3). The program directory that is provided in softcopy format on the CBPDO tape is identical to the hardcopy format if one was included with your order. All service and HOLDDATA for Developer for z Systems Host Utilities are included on the CBPDO tape.

Do not use this program directory if you install Developer for z Systems Host Utilities with a SystemPac or ServerPac. When you use one of those offerings, use the jobs and documentation supplied with the offering. The offering will point you to specific sections of this program directory as needed.

1.1 Developer for z Systems Host Utilities Description

Similar to functions available on the IBM Developer for z Systems client, IBM Developer for z Systems Host Utilities provides code analysis tools. A benefit of doing code analysis on the host is that it can be integrated in your daily batch processing.

1.2 Developer for z Systems Host Utilities FMIDs

Developer for z Systems Host Utilities consists of the following FMIDs:

HAKGE10

2.0 Program Materials

An IBM program is identified by a program number.

Developer for z Systems Host Utilities is available as a component of multiple products. Depending on which product you acquired, different functions of Developer for z Systems Host Utilities will be enabled or disabled.

- IBM Developer for z Systems V14.1.0, program number 5724-T07 (web download)
- IBM Developer for z Systems Enterprise Edition V14.1.0, program number 5655-AC5 (Shopz orderable)

Basic Machine-Readable Materials are materials that are supplied under the base license and are required for the use of the product.

The program announcement material describes the features supported by Developer for z Systems Host Utilities. Ask your IBM representative for this information if you have not already received a copy.

2.1 Basic Machine-Readable Material

The distribution medium for this program is physical media or downloadable files. This program is in SMP/E RELFILE format and is installed by using SMP/E. See 6.0, “Installation Instructions” on page 16 for more information about how to install the program.

The rest of this section only applies when Developer for z Systems Host Utilities is ordered via Shopz. It does not apply when you downloaded it from the web.

Select this link to go to the next section: 2.2, “Optional Machine-Readable Material” on page 4

You can find information about the physical media for the basic machine-readable materials for Developer for z Systems Host Utilities in the *CBPDO Memo To Users Extension*.

Figure 1 describes the program file content for Developer for z Systems Host Utilities. You can refer to the *CBPDO Memo To Users Extension* to see where the files reside on the tape.

Notes:

1. The data set attributes in this table must be used in the JCL of jobs that read the data sets. However, because the data sets are in IEBCOPY unloaded format, their actual attributes might be different.
2. If any RELFILES are identified as PDSEs, ensure that SMPTLIB data sets are allocated as PDSEs.

Figure 1. Program File Content

Name	O R G	R E C F M	L R E C L	BLK SIZE
SMPMCS	SEQ	FB	80	8800
IBM.HAKGE10.F1	PDSE	FB	80	8800
IBM.HAKGE10.F2	PDSE	FB	80	8800
IBM.HAKGE10.F3	PDSE	VB	8796	8800
IBM.HAKGE10.F4	PDSE	VB	8796	8800
IBM.HAKGE10.F5	PDSE	VB	8796	8800
IBM.HAKGE10.F6	PDSE	VB	8796	8800

2.2 Optional Machine-Readable Material

No optional machine-readable materials are provided for Developer for z Systems Host Utilities.

2.3 Program Publications

The following sections identify the basic publications for Developer for z Systems Host Utilities.

Figure 2 identifies the basic unlicensed program publications for Developer for z Systems Host Utilities. Those that are in softcopy format publications can be obtained from the IBM Publications Center website at <http://www.ibm.com/shop/publications/order/>.

Figure 2. Basic Material: Unlicensed

Publication Title	Form Number	Media Format
<i>IBM Developer for z Systems Host Configuration Guide</i>	SC27-8577	See note ¹
<i>IBM Developer for z Systems Host Configuration Reference</i>	SC27-8578	See note ¹
<i>IBM Developer for z Systems Messages and Codes</i>	SC14-7497	See note ¹
Note:		
1. These, and other, publications can be obtained from the Developer for z Systems online library, http://www-01.ibm.com/support/docview.wss?uid=swg27048563 .		
2. Requisite information can be obtained by creating a report for Developer for z Systems Host Utilities on http://www.ibm.com/software/reports/compatibility/clarity/index.html .		

2.3.1 Optional Program Publications

No optional publications are provided for Developer for z Systems Host Utilities.

2.4 Program Source Materials

No program source materials or viewable program listings are provided for Developer for z Systems Host Utilities.

2.5 Publications Useful During Installation

You might want to use the publications listed in Figure 3 during the installation of Developer for z Systems Host Utilities.

<i>Figure 3. Publications Useful During Installation</i>		
Publication Title	Form Number	Media Format
<i>IBM SMP/E for z/OS User's Guide</i>	SA22-7773	http://www.ibm.com/shop/publications/order/
<i>IBM SMP/E for z/OS Commands</i>	SA22-7771	http://www.ibm.com/shop/publications/order/
<i>IBM SMP/E for z/OS Reference</i>	SA22-7772	http://www.ibm.com/shop/publications/order/
<i>IBM SMP/E for z/OS Messages, Codes, and Diagnosis</i>	GA22-7770	http://www.ibm.com/shop/publications/order/

3.0 Program Support

This section describes the IBM support available for Developer for z Systems Host Utilities. The service number for Developer for z Systems Host Utilities is 0513891.

3.1 Program Services

Contact your IBM representative for specific information about available program services.

3.2 Preventive Service Planning

Before you install Developer for z Systems Host Utilities, make sure that you have reviewed the current Preventive Service Planning (PSP) information. Review the PSP Bucket for General Information, Installation Documentation, and the Cross Product Dependencies sections. For the Recommended Service section, instead of reviewing the PSP Bucket, it is recommended you use the IBM.ProductInstall-RequiredService fix category in SMP/E to ensure you have all the recommended service installed. Use the **FIXCAT(IBM.PRODUCTINSTALL-REQUIRESERVICE)** operand on the **APPLY CHECK** command. See 6.1.14, "Perform SMP/E APPLY" on page 25 for a sample APPLY command

If you obtained Developer for z Systems Host Utilities as part of a CBPDO, HOLDDATA is included.

If the CBPDO for Developer for z Systems Host Utilities is older than two weeks by the time you install the product materials, you can obtain the latest PSP Bucket information by going to the following website:

<http://www14.software.ibm.com/webapp/set2/psearch/search?domain=psp>

You can also use S/390 SoftwareXcel or contact the IBM Support Center to obtain the latest PSP Bucket information.

For program support, access the Software Support Website at <http://www-01.ibm.com/software/support/>.

PSP Buckets are identified by UPGRADEs, which specify product levels; and SUBSETs, which specify the FMIDs for a product level. The UPGRADE and SUBSET values for Developer for z Systems Host Utilities are included in Figure 4.

Figure 4. PSP Upgrade and Subset ID

UPGRADE	SUBSET	Description
IDZE10	HAKGE10	Developer for z Systems Host Utilities

3.3 Statement of Support Procedures

Report any problems which you feel might be an error in the product materials to your IBM Support Center. You may be asked to gather and submit additional diagnostics to assist the IBM Support Center in their analysis.

Figure 5 on page 7 identifies the component IDs (COMPID) for Developer for z Systems Host Utilities.

<i>Figure 5. Component IDs</i>			
FMID	COMPID	Component Name	RETAIN Release
HAKGE10	5724T0733	Developer for z Systems Host Utilities	E10

4.0 Program and Service Level Information

This section identifies the program and relevant service levels of Developer for z Systems Host Utilities. The program level refers to the APAR fixes that have been incorporated into the program. The service level refers to the PTFs that have been incorporated into the program.

4.1 Program Level Information

All resolved APARs of previous releases of Developer for z Systems Host Utilities have been incorporated into Developer for z Systems Host Utilities.

4.2 Service Level Information

No PTFs against this release of Developer for z Systems Host Utilities have been incorporated into the product package.

Frequently check the Developer for z Systems Host Utilities PSP Bucket for HIPER and SPECIAL attention PTFs against all FMIDs that you must install. You can also receive the latest HOLDDATA, then add the **FIXCAT(IBM.PRODUCTINSTALL-REQUIRESERVICE)** operand on your **APPLY CHECK** command. This will allow you to review the recommended and critical service that should be installed with your FMIDs.

5.0 Installation Requirements and Considerations

The following sections identify the system requirements for installing and activating Developer for z Systems Host Utilities. The following terminology is used:

- *Driving system*: the system on which SMP/E is executed to install the program.
The program might have specific operating system or product level requirements for using processes, such as binder or assembly utilities during the installation.
- *Target system*: the system on which the program is configured and run.
The program might have specific product level requirements, such as needing access to the library of another product for link-edits. These requirements, either mandatory or optional, might directly affect the element during the installation or in its basic or enhanced operation.

In many cases, you can use a system as both a driving system and a target system. However, you can make a separate IPL-able clone of the running system to use as a target system. The clone must include copies of all system libraries that SMP/E updates, copies of the SMP/E CSI data sets that describe the system libraries, and your PARMLIB and PROCLIB.

Use separate driving and target systems in the following situations:

- When you install a new level of a product that is already installed, the new level of the product will replace the old one. By installing the new level onto a separate target system, you can test the new level and keep the old one in production at the same time.
- When you install a product that shares libraries or load modules with other products, the installation can disrupt the other products. By installing the product onto a separate target system, you can assess these impacts without disrupting your production system.

5.1 Driving System Requirements

This section describes the environment of the driving system required to install Developer for z Systems Host Utilities.

5.1.1 Machine Requirements

The driving system can run in any hardware environment that supports the required software.

5.1.2 Programming Requirements

Figure 6. Driving System Software Requirements

Program Number	Product Name	Minimum VRM	Minimum Service Level will satisfy these APARs	Included in the shipped product?
5650-ZOS	z/OS	V02.01.00 or higher	N/A	No

Note: SMP/E is a requirement for Installation and is an element of z/OS but can also be ordered as a separate product, 5655-G44, minimally V03.06.00.

Note: Installation might require migration to new z/OS releases to be service supported. See http://www-03.ibm.com/systems/z/os/zos/support/zos_eos_dates.html.

Developer for z Systems Host Utilities is installed into a file system, either HFS or zFS. Before installing Developer for z Systems Host Utilities, you must ensure that the target system file system data sets are available for processing on the driving system. OMVS must be active on the driving system and the target system file data sets must be mounted on the driving system.

If you plan to install Developer for z Systems Host Utilities in a zFS file system, this requires that zFS be active on the driving system. Information on activating and using zFS can be found in z/OS Distributed File Service zSeries File System Administration, SC24-5989.

5.2 Target System Requirements

This section describes the environment of the target system required to install and use Developer for z Systems Host Utilities.

Developer for z Systems Host Utilities installs in the z/OS (Z038) SREL.

5.2.1 Machine Requirements

The target system can run in any hardware environment that supports the required software.

5.2.2 Programming Requirements

5.2.2.1 Installation Requisites

Installation requisites identify products that are required and *must* be present on the system or products that are not required but *should* be present on the system for the successful installation of this product.

Mandatory installation requisites identify products that are required on the system for the successful installation of this product. These products are specified as PREs or REQs.

Developer for z Systems Host Utilities has no mandatory installation requisites.

Conditional installation requisites identify products that are *not* required for successful installation of this product but can resolve such things as certain warning messages at installation time. These products are specified as IF REQs.

Developer for z Systems Host Utilities has no conditional installation requisites.

5.2.2.2 Operational Requisites

Operational requisites are products that are required and *must* be present on the system or products that are not required but *should* be present on the system for this product to operate all or part of its functions.

Mandatory operational requisites identify products that are required for this product to operate its basic functions. These products are specified as PREs or REQs.

Developer for z Systems Host Utilities has no mandatory operational requisites.

Conditional operational requisites identify products that are *not* required for this product to operate its basic functions but are required at run time for this product to operate specific functions. These products are specified as IF REQs.

Developer for z Systems Host Utilities has no conditional operational requisites. However, the product in which you received Developer for z Systems Host Utilities contains multiple FMIDs, some of which provide services utilized by Developer for z Systems Host Utilities. See 6.4, “Product FMIDs” on page 28 for details.

5.2.2.3 Toleration/Coexistence Requisites

Toleration/coexistence requisites identify products that must be present on sharing systems. These systems can be other systems in a multisystem environment (not necessarily sysplex), a shared DASD environment (such as test and production), or systems that reuse the same DASD environment at different time intervals.

Developer for z Systems Host Utilities has no toleration/coexistence requisites.

5.2.2.4 Incompatibility (Negative) Requisites

Negative requisites identify products that must *not* be installed on the same system as this product.

Developer for z Systems Host Utilities has no negative requisites.

5.2.3 DASD Storage Requirements

Developer for z Systems Host Utilities libraries can reside on all supported DASD types.

Figure 7 on page 12 lists the total space that is required for each type of library.

<i>Figure 7. Total DASD Space Required by Developer for z Systems Host Utilities</i>		
Library Type	Total Space Required in 3390 Trks	Description
Target	35 Tracks	
Distribution	21480 Tracks	
File System(s)	43500 Tracks	
Web Download	33839 Tracks	This row only applies when Developer for z Systems Host Utilities is downloaded from the web. It does not apply when you ordered it via Shopz. These are temporary data sets, which can be removed after the SMP/E install.

Notes:

1. For non-RECFM U data sets, IBM recommends using system-determined block sizes for efficient DASD utilization. For RECFM U data sets, IBM recommends using a block size of 32760, which is most efficient from the performance and DASD utilization perspective.

2. Abbreviations used for data set types are shown as follows.

- U** Unique data set, allocated by this product and used by only this product. This table provides all the required information to determine the correct storage for this data set. You do not need to refer to other tables or program directories for the data set size.
- S** Shared data set, allocated by this product and used by this product and other products. To determine the correct storage needed for this data set, add the storage size given in this table to those given in other tables (perhaps in other program directories). If the data set already exists, it must have enough free space to accommodate the storage size given in this table.
- E** Existing shared data set, used by this product and other products. This data set is *not* allocated by this product. To determine the correct storage for this data set, add the storage size given in this table to those given in other tables (perhaps in other program directories). If the data set already exists, it must have enough free space to accommodate the storage size given in this table.

If you currently have a previous release of this product installed in these libraries, the installation of this release will delete the old release and reclaim the space that was used by the old release and any service that had been installed. You can determine whether these libraries have enough space by deleting the old release with a dummy function, compressing the libraries, and comparing the space requirements with the free space in the libraries.

For more information about the names and sizes of the required data sets, see 6.1.10, "Allocate SMP/E Target and Distribution Libraries" on page 23.

3. Abbreviations used for the file system path type are as follows.

- N** New path, created by this product.
- X** Path created by this product, but might already exist from a previous release.
- P** Previously existing path, created by another product.

4. All target and distribution libraries listed have the following attributes:

- The default name of the data set can be changed.
- The default block size of the data set can be changed.
- The data set can be merged with another data set that has equivalent characteristics.
- The data set can be either a PDS or a PDSE, with some exceptions. If the value in the "ORG" column specifies "PDS", the data set must be a PDS. If the value in "DIR Blks" column specifies "N/A", the data set must be a PDSE.

5. All target libraries listed have the following attributes:

- These data sets can be SMS-managed, but they are not required to be SMS-managed.
- These data sets are not required to reside on the IPL volume.
- The values in the "Member Type" column are not necessarily the actual SMP/E element types that are identified in the SMPMCS.

6. All target libraries that are listed and contain load modules have the following attributes:

- These data sets can be in the LPA, but they are not required to be in the LPA.
- These data sets can be in the LNKLIST.
- These data sets are not required to be APF-authorized, with some exceptions. If the value in the "Member Type" column specifies "APF", the data set must be APF-authorized.

Figure 8. Storage Requirements for SMP/E Work Data Sets

Library DDNAME	T Y P E	O R G	R E C F M	L R E C L	No. of 3390 Trks	No. of DIR Blks
SMPWRK6	S	PDS	FB	80	(20,200)	10
SYSUT1	U	SEQ	--	--	(20,200)	0

Figure 9. Storage Requirements for SMP/E Data Sets

Library DDNAME	T Y P E	O R G	R E C F M	L R E C L	No. of 3390 Trks	No. of DIR Blks
SMPPTS	S	PDSE	FB	80	21450	10

The following figures describe the target and distribution libraries and file system paths required to install Developer for z Systems Host Utilities. The storage requirements of Developer for z Systems Host Utilities must be added to the storage required by other programs that have data in the same library or path.

Note: Use the data in these tables to determine which libraries can be merged into common data sets. In addition, since some ALIAS names may not be unique, ensure that no naming conflicts will be introduced before merging libraries.

Figure 10. Storage Requirements for Developer for z Systems Host Utilities Target Libraries

Library DDNAME	Member Type	Target Volume	T Y P E	O R G	R E C F M	L R E C L	No. of 3390 Trks	No. of DIR Blks
SAKGPROC	REXX	ANY	U	PDSE	FB	80	20	5
SAKGSAMP	Samples	ANY	U	PDSE	FB	80	15	5

Figure 11. Developer for z Systems Host Utilities File System Paths

DDNAME	T Y P E	Path Name
SAKGZFS	X	/usr/lpp/IBM/idzutil/IBM

Figure 12. Storage Requirements for Developer for z Systems Host Utilities Distribution Libraries

Library DDNAME	T Y P E	O R G	R E C F M	L R E C L	No. of 3390 Trks	No. of DIR Blks
AAKGSAMP	U	PDSE	FB	80	30	10
AAKGZFS	U	PDSE	VB	8796	21450	21450

The rest of this section only applies when Developer for z Systems Host Utilities is downloaded from the web. It does not apply when you ordered it via Shopz.

Select this link to go to the next section: 5.3, "FMIDs Deleted" on page 15

The following figures list data sets that are not used by Developer for z Systems Host Utilities, but are required as input for SMP/E.

Figure 13. Storage Requirements for Developer for z Systems Host Utilities Web Download Data Sets

Data Set Name	T Y P E	O R G	R E C F M	L R E C L	No. of 3390 Trks	No. of DIR Blks
hlq.IBM.HAKGE10.F1	U	PDSE	FB	80	6	N/A
hlq.IBM.HAKGE10.F2	U	PDSE	FB	80	15	N/A
hlq.IBM.HAKGE10.F3	U	PDSE	VB	8796	2057	N/A
hlq.IBM.HAKGE10.F4	U	PDSE	U	0	5977	N/A
hlq.IBM.HAKGE10.F5	U	PDSE	VB	256	5988	N/A
hlq.IBM.HAKGE10.F6	U	PDSE	VB	256	6069	N/A
hlq.IBM.HAKGE10.SMPMCS	U	SEQ	FB	80	1	N/A
z/OS UNIX file system	U	zFS	N/A	N/A	35687	N/A
Note: These are temporary data sets, which can be removed after the SMP/E install.						

5.3 FMIDs Deleted

Installing Developer for z Systems Host Utilities might result in the deletion of other FMIDs. To see which FMIDs will be deleted, examine the ++VER statement in the SMPMCS of the product.

If you do not want to delete these FMIDs at this time, install Developer for z Systems Host Utilities into separate SMP/E target and distribution zones.

Note: These FMIDs are not automatically deleted from the Global Zone. If you want to delete these FMIDs from the Global Zone, use the SMP/E REJECT NOFMID DELETEFMID command. See the SMP/E Commands book for details.

5.4 Special Considerations

Developer for z Systems Host Utilities has no special considerations for the target system.

6.0 Installation Instructions

This chapter describes the installation method and the step-by-step procedures to install and to activate the functions of Developer for z Systems Host Utilities.

Please note the following points:

- If you want to install Developer for z Systems Host Utilities into its own SMP/E environment, consult the SMP/E manuals for instructions on creating and initializing the SMP/CSI and the SMP/E control data sets.
- You can use the sample jobs that are provided to perform part or all of the installation tasks. The SMP/E jobs assume that all DDDEF entries that are required for SMP/E execution have been defined in appropriate zones.
- You can use the SMP/E dialogs instead of the sample jobs to accomplish the SMP/E installation steps.

6.1 Installing Developer for z Systems Host Utilities

6.1.1 SMP/E Considerations for Installing Developer for z Systems Host Utilities

Use the SMP/E RECEIVE, APPLY, and ACCEPT commands to install this release of Developer for z Systems Host Utilities.

6.1.2 SMP/E Options Subentry Values

The recommended values for certain SMP/E CSI subentries are shown in Figure 14. Using values lower than the recommended values can result in failures in the installation. DSSPACE is a subentry in the GLOBAL options entry. PEMAX is a subentry of the GENERAL entry in the GLOBAL options entry. See the SMP/E manuals for instructions on updating the global zone.

Figure 14. SMP/E Options Subentry Values

Subentry	Value	Comment
DSSPACE	(1200,1200,1400)	Space allocation
PEMAX	SMP/E Default	IBM recommends using the SMP/E default for PEMAX.

6.1.3 Overview of the installation steps

Overview of steps required to install IBM Developer for z Systems Host Utilities.

1. Allocate file system to hold web download package
(only applicable for web download, not Shopz orders)
2. Upload the web download package to the host
(only applicable for web download, not Shopz orders)
3. Extract and expand the compressed SMPMCS and RELFILEs
(only applicable for web download, not Shopz orders)

Select this link to skip the web download specific steps: 6.1.7, “Sample Jobs” on page 21

4. Create SMP/E environment (optional)
5. Perform SMP/E RECEIVE
6. Allocate SMP/E target and distribution libraries
7. Allocate and mount z/OS UNIX file system (optional)
8. Allocate z/OS UNIX paths
9. Create DDDEF entries
10. Perform SMP/E APPLY
11. Perform SMP/E ACCEPT
12. Run REPORT CROSSZONE

6.1.4 Allocate file system to hold web download package

This section only applies when Developer for z Systems Host Utilities is downloaded from the web. It does not apply when it is ordered via Shopz.

Select this link to skip the web download specific steps: 6.1.7, “Sample Jobs” on page 21

The SMP/E input data sets to install IBM Developer for z Systems Host Utilities are provided as compressed files in HAKGE10.pax.Z, which must be uploaded to z/OS as a z/OS UNIX file. You can either create a new z/OS UNIX file system (zFS) or create a new directory in an existing file system to place HAKGE10.pax.Z.

You can use the following sample JCL to create a new file system, and directory, for the download package.

```

//FILESYS JOB <job information>
//*
//* - Provide valid job card information
//* - Change:
//*   @zfs_path@
//*   ----+----1----+----2----+----3----+----4----+----5
//*           - To the absolute z/OS UNIX path for the download
//*             package (starting with /)
//*           - Maximum length is 50 characters
//*           - Do not include a trailing /
//*   @zfs_dsn@
//*           - To your file system data set name
//*
//* Your userid MUST be defined as a SUPERUSER to successfully
//* run this job
//*
//CREATE EXEC PGM=IDCAMS,REGION=0M,COND=(0,LT)
//SYSPRINT DD SYSOUT=*
//SYSIN DD *
  DEFINE CLUSTER ( -
    NAME(@zfs_dsn@) -
    TRK(35687 10) -
    LINEAR -
    SHAREOPTIONS(3) -
  )
//*
//      SET ZFSDSN=@zfs_dsn@
//FORMAT EXEC PGM=IOEAGFMT,REGION=0M,COND=(0,LT),
//      PARM='-aggregate &ZFSDSN -compat'
//*STEPLIB DD DISP=SHR,DSN=IOE.SIOELMOD      before z/OS 1.13
//*STEPLIB DD DISP=SHR,DSN=SYS1.SIEALNKE     from z/OS 1.13
//SYSPRINT DD SYSOUT=*
//*
//MOUNT EXEC PGM=IKJEFT01,REGION=0M,COND=(0,LT)
//SYSEXEC DD DISP=SHR,DSN=SYS1.SBPXEXEC
//SYSTSPRT DD SYSOUT=*
//SYSTSIN DD *
  PROFILE MSGID WTPMSG
  oshell umask 0022; +
  mkdir -p @zfs_path@
  MOUNT +
  FILESYSTEM('@zfs_dsn@') +
  MOUNTPOINT('@zfs_path@') +
  MODE(RDWR) TYPE(ZFS) PARM('AGGRGROW')
//*

```

Expected Return Codes and Messages: You will receive a return code of 0 if this job runs correctly.

6.1.5 Upload the web download package to the host

This section only applies when Developer for z Systems Host Utilities is downloaded from the web. It does not apply when it is ordered via Shopz.

Select this link to skip the web download specific steps: 6.1.7, “Sample Jobs” on page 21

Upload the HAKGE10.readme.txt file in text format and the HAKGE10.pax.Z file in binary format from your workstation to the z/OS UNIX file system.

In the following sample dialog, we use FTP from a Microsoft Windows command line to do the transfer. Commands or other information entered by the user are in bold, and the following values are assumed:

<i>Figure 15. User Entered Values</i>	
User enters:	Values
mvsaddr	TCP/IP address or hostname of the z/OS system
tsouid	Your TSO user ID
tsopw	Your TSO password
d:	Location of the downloaded files
@zfs_path@	z/OS UNIX path where to store the files. This matches the @zfs_path@ variable you specified in the previous step.

```
C:\>ftp mvsaddr
Connected to mvsaddr.
220-FTPDI IBM FTP CS %version% at mvsaddr, %time% on %date%.
220 Connection will close if idle for more than 5 minutes.
User (mvsaddr:(none)): tsouid
331 Send password please.
Password: tsopw
230 tsouid is logged on. Working directory is "tsouid.".
ftp> cd @zfs_path@
250 HFS directory @zfs_path@ is the current working directory
ftp> ascii
200 Representation type is Ascii NonPrint
ftp> put d:\HAKGE10.readme.txt
200 Port request OK.
125 Storing data set @zfs_path@/HAKGE10.readme.txt
250 Transfer completed successfully.
ftp: 19521 bytes sent in 0.01 sec. (1366.67 Kb/s)
ftp> binary
200 Representation type is Image
ftp> put d:\HAKGE10.pax.Z
200 Port request OK.
125 Storing data set @zfs_path@/HAKGE10.pax.Z
250 Transfer completed successfully.
ftp: 1092284928 bytes sent in 1.26 sec. (1040.52 Kb/s)
```

```
ftp> quit
221 Quit command received. Goodbye.
```

6.1.6 Extract and expand the compressed SMPMCS and RELFILES

This section only applies when Developer for z Systems Host Utilities is downloaded from the web. It does not apply when it is ordered via Shopz.

Select this link to skip the web download specific steps: 6.1.7, “Sample Jobs” on page 21

The HAKGE10.readme.txt file uploaded in the previous step holds a sample JCL to expand the compressed SMPMCS and RELFILES from the uploaded HAKGE10.pax.Z file into data sets for use by the SMP/E RECEIVE job. The JCL is repeated here for your convenience.

- @zfs_path@ matches the variable you specified in the previous step.
- If the 'oshell' command gets a RC=256 and message "pax: checksum error on tape (got ee2e, expected 0)", then the archive file was not uploaded to the host in binary format.
- GIMUNZIP allocates data sets to match the definitions of the original data sets. You may encounter errors if your SMS ACS routines alter the attributes used by GIMUNZIP. If this occurs, specify a non-SMS managed volume for the GIMUNZIP allocation of the data sets. For example:

```
<ARCHDEF archid="..."
  storclas="storage_class" volume="data_set_volume"
  newname="..."/>
```

```
//EXTRACT JOB <job information>
//*
//* - Provide valid job card information
//* - Change:
//*   @PREFIX@
//*   ----+-----1-----+-----2-----+
//*           - To your desired data set name prefix
//*           - Maximum length is 25 characters
//*           - This value is used for the names of the
//*             data sets extracted from the download-package
//*   @zfs_path@
//*   ----+-----1-----+-----2-----+-----3-----+-----4-----+-----5
//*           - To the absolute z/OS UNIX path for the
//*             download-package (starting with /)
//*           - Maximum length is 50 characters
//*           - Do not include a trailing /
//*
//UNPAX EXEC PGM=IKJEFT01,REGION=0M,COND=(0,LT)
//SYSEXEC DD DISP=SHR,DSN=SYS1.SBPXEXEC
//SYSTSPRT DD SYSOUT=*
//SYSTSIN DD *
```



```

    oshell cd @zfs_path@/ ; +
    pax -rvf HAKGE10.pax.Z
//*
//GIMUNZIP EXEC PGM=GIMUNZIP,REGION=0M,COND=(0,LT)
//*STEPLIB DD DISP=SHR,DSN=SYS1.MIGLIB
//SYSUT3 DD UNIT=SYSALLDA,SPACE=(CYL,(50,10))
//SYSUT4 DD UNIT=SYSALLDA,SPACE=(CYL,(25,5))
//SMPDOUT DD SYSOUT=*
//SYSPRINT DD SYSOUT=*
//SMPDIR DD PATHDISP=KEEP,
// PATH='@zfs_path@/'
//SYSIN DD *

<GIMUNZIP>
<ARCHDEF archid="SMPMCS"
    newname="@PREFIX@.IBM.HAKGE10.SMPMCS"/>
<ARCHDEF archid="IBM.HAKGE10.F1"
    newname="@PREFIX@.IBM.HAKGE10.F1"/>
<ARCHDEF archid="IBM.HAKGE10.F2"
    newname="@PREFIX@.IBM.HAKGE10.F2"/>
<ARCHDEF archid="IBM.HAKGE10.F3"
    newname="@PREFIX@.IBM.HAKGE10.F3"/>
<ARCHDEF archid="IBM.HAKGE10.F4"
    newname="@PREFIX@.IBM.HAKGE10.F4"/>
<ARCHDEF archid="IBM.HAKGE10.F5"
    newname="@PREFIX@.IBM.HAKGE10.F5"/>
<ARCHDEF archid="IBM.HAKGE10.F6"
    newname="@PREFIX@.IBM.HAKGE10.F6"/>
</GIMUNZIP>
//*
```

6.1.7 Sample Jobs

The following sample installation jobs are provided as part of the product to help you install Developer for z Systems Host Utilities:

<i>Figure 16 (Page 1 of 2). Sample Installation Jobs</i>			
Job Name	Job Type	Description	RELFILE
AKG1SMPE	SMP/E	Sample job to create an SMP/E environment (optional)	IBM.HAKGE10.F1
AKG2RCVE	RECEIVE	Sample SMP/E RECEIVE job	IBM.HAKGE10.F1
AKG3ALOC	ALLOCATE	Sample job to allocate target and distribution libraries	IBM.HAKGE10.F1
AKG4ZFS	ALLOMZFS	Sample job to allocate, create mountpoint, and mount zFS data sets	IBM.HAKGE10.F1

Figure 16 (Page 2 of 2). Sample Installation Jobs

Job Name	Job Type	Description	RELFILE
AKG5MKD	MKDIR	Sample job to invoke the supplied AKGMKDIR EXEC to allocate file system paths	IBM.HAKGE10.F1
AKG6DDEF	DDDEF	Sample job to define SMP/E DDDEFs	IBM.HAKGE10.F1
AKG7APLY	APPLY	Sample SMP/E APPLY job	IBM.HAKGE10.F1
AKG8ACPT	ACCEPT	Sample SMP/E ACCEPT job	IBM.HAKGE10.F1
<p>Note: When Developer for z Systems Host Utilities is downloaded from the web, the RELFILE data set name will be prefixed by your chosen high level qualifier, as documented in section 6.1.6, "Extract and expand the compressed SMPMCS and RELFILES" on page 20.</p>			

The rest of this section only applies when Developer for z Systems Host Utilities is ordered via Shopz. It does not apply when you downloaded it from the web. Select this link to go to the next section: [6.1.8, "Create SMP/E environment \(optional\)" on page 23](#)

You can access the sample installation jobs by performing an SMP/E RECEIVE (refer to 6.1.9, "Perform SMP/E RECEIVE" on page 23) then copy the jobs from the RELFILES to a work data set for editing and submission. See Figure 16 on page 21 to find the appropriate relfile data set.

You can also copy the sample installation jobs from the tape or product files by submitting the following job. Depending on your distribution medium, use either the //TAPEIN or the //FILEIN DD statement and comment out or delete the other statement. Before you submit the job, add a job card and change the lowercase parameters to uppercase values to meet the requirements of your site.

```
//STEP1 EXEC PGM=IEBCOPY
//SYSPRINT DD SYSOUT=*
//TAPEIN DD DSN=IBM.HAKGE10.F1,
// DISP=(OLD,KEEP),
// LABEL=(x,SL),
// VOL=SER=volser,
// UNIT=tunit
//FILEIN DD DSN=IBM.HAKGE10.F1,
// DISP=SHR,
//* VOL=SER=filevol,
// UNIT=SYSALLDA
//OUT DD DSNAME=jc1-library-name,
// DISP=(NEW,CATLG,DELETE),
// SPACE=(TRK,(6,5,5)),
//* VOL=SER=dasdvol,
// UNIT=SYSALLDA
//SYSUT3 DD UNIT=SYSALLDA,SPACE=(CYL,(1,1))
//SYSIN DD *
COPY INDD=xxxxIN,OUTDD=OUT
/*
```

See the following information to update the statements in the previous sample:

TAPEIN:

tunit is the unit value that matches the product package.

volser is the volume serial that matches the product package.

x is the tape file number that indicates the location of the data set name on the tape.

See the documentation that is provided by CBPDO for the location of IBM.HAKGE10.F1 on the tape.

FILEIN:

filevol is the volume serial of the DASD device where the downloaded files reside.

OUT:

jcl-library-name is the name of the output data set where the sample jobs are stored.

dasdvol is the volume serial of the DASD device where the output data set resides. Uncomment the statement if a volume serial must be provided.

SYSIN:

xxxxIN is either TAPEIN or FILEIN depending on your input DD statement.

6.1.8 Create SMP/E environment (optional)

If you are using an existing CSI, do not run the sample job AKG1SMPE.

If you choose to create a new SMP/E environment for this install, a sample job is provided or you may choose to use your own JCL. If you choose to use the sample job provided, edit and submit AKG1SMPE. Consult the instructions in the sample job for more information.

Expected Return Codes and Messages: You will receive a return code of 0 if this job runs correctly.

6.1.9 Perform SMP/E RECEIVE

If you have obtained Developer for z Systems Host Utilities as part of a CBPDO, use the RCVPDO job in the CBPDO RIMLIB data set to receive the Developer for z Systems Host Utilities FMIDs, service, and HOLDDATA that are included on the CBPDO package. For more information, see the documentation that is included in the CBPDO.

You can also choose to edit and submit sample job AKG2RCVE to perform the SMP/E RECEIVE for Developer for z Systems Host Utilities. Consult the instructions in the sample job for more information.

Expected Return Codes and Messages: You will receive a return code of 0 if this job runs correctly.

6.1.10 Allocate SMP/E Target and Distribution Libraries

Edit and submit sample job AKG3ALOC to allocate the SMP/E target and distribution libraries for Developer for z Systems Host Utilities. Consult the instructions in the sample job for more information.

Expected Return Codes and Messages: You will receive a return code of 0 if this job runs correctly.

6.1.11 Allocate, create and mount ZFS Files (Optional)

This job allocates, creates a mountpoint, and mounts zFS data sets.

If you plan to install Developer for z Systems Host Utilities into a new z/OS UNIX file system, you can edit and submit the optional AKG4ZFS job to perform the following tasks:

- Create the z/OS UNIX file system
- Create a mountpoint
- Mount the z/OS UNIX file system on the mountpoint

Consult the instructions in the sample job for more information.

The recommended z/OS UNIX file system type is zFS. The recommended mountpoint is */usr/lpp/IBM/idzutil*.

Before running the sample job to create the z/OS UNIX file system, you must ensure that OMVS is active on the driving system. zFS must be active on the driving system if you are installing Developer for z Systems Host Utilities into a file system that is zFS.

If you create a new file system for this product, consider updating the BPXPRMxx PARMLIB member to mount the new file system at IPL time. This action can be helpful if an IPL occurs before the installation is completed.

```
MOUNT FILESYSTEM('#dsn')
MOUNTPOINT('/usr/lpp/IBM/idzutil')
MODE(RDWR) /* can be MODE(READ) */
TYPE(ZFS) PARM('AGGRGROW') /* zFS, with extents */
```

See the following information to update the statements in the previous sample:

#dsn is the name of the data set holding the z/OS UNIX file system.

/usr/lpp/IBM/idzutil is the name of the mountpoint where the z/OS UNIX file system will be mounted.

Expected Return Codes and Messages: You will receive a return code of 0 if this job runs correctly.

6.1.12 Allocate File System Paths

The target system HFS or zFS data set must be mounted on the driving system when running the sample AKG5MKD job since the job will create paths in the HFS or zFS.

Before running the sample job to create the paths in the file system, you must ensure that OMVS is active on the driving system and that the target system's HFS or zFS file system is mounted to the driving system. zFS must be active on the driving system if you are installing Developer for z Systems Host Utilities into a file system that is zFS.

If you plan to install Developer for z Systems Host Utilities into a new HFS or zFS file system, you must create the mountpoint and mount the new file system to the driving system for Developer for z Systems Host Utilities.

The recommended mountpoint is `/usr/lpp/IBM/idzutil`.

Edit and submit sample job AKG5MKD to allocate the HFS or zFS paths for Developer for z Systems Host Utilities. Consult the instructions in the sample job for more information.

If you create a new file system for this product, consider updating the BPXPRMxx PARMLIB member to mount the new file system at IPL time. This action can be helpful if an IPL occurs before the installation is completed.

Expected Return Codes and Messages: You will receive a return code of 0 if this job runs correctly.

6.1.13 Create DDDEF Entries

Edit and submit sample job AKG6DDEF to create DDDEF entries for the SMP/E target and distribution libraries for Developer for z Systems Host Utilities. Consult the instructions in the sample job for more information.

Expected Return Codes and Messages: You will receive a return code of 0 if this job runs correctly.

6.1.14 Perform SMP/E APPLY

1. Ensure that you have the latest HOLDDATA; then edit and submit sample job AKG7APLY to perform an SMP/E APPLY CHECK for Developer for z Systems Host Utilities. Consult the instructions in the sample job for more information.

The latest HOLDDATA is available through several different portals, including <http://service.software.ibm.com/holddata/390holddata.html>. The latest HOLDDATA may identify HIPER and FIXCAT APARs for the FMIDs you will be installing. An APPLY CHECK will help you determine if any HIPER or FIXCAT APARs are applicable to the FMIDs you are installing. If there are any applicable HIPER or FIXCAT APARs, the APPLY CHECK will also identify fixing PTFs that will resolve the APARs, if a fixing PTF is available.

You should install the FMIDs regardless of the status of unresolved HIPER or FIXCAT APARs. However, do not deploy the software until the unresolved HIPER and FIXCAT APARs have been analyzed to determine their applicability. That is, before deploying the software either ensure fixing PTFs are applied to resolve all HIPER or FIXCAT APARs, or ensure the problems reported by all HIPER or FIXCAT APARs are not applicable to your environment.

To receive the full benefit of the SMP/E Causer SYSMOD Summary Report, do *not* bypass the PRE, ID, REQ, and IFREQ on the APPLY CHECK. The SMP/E root cause analysis identifies the cause only of *errors* and not of *warnings* (SMP/E treats bypassed PRE, ID, REQ, and IFREQ conditions as warnings, instead of errors).

Here are sample APPLY commands:

- a. To ensure that all recommended and critical service is installed with the FMIDs, receive the latest HOLDDATA and use the APPLY CHECK command as follows

```
APPLY S(fmid,fmid,...) CHECK
FORFMID(fmid,fmid,...)
SOURCEID(RSU*)
FIXCAT(IBM.ProductInstall-RequiredService)
GROUPEXTEND .
```

Some HIPER APARs might not have fixing PTFs available yet. You should analyze the symptom flags for the unresolved HIPER APARs to determine if the reported problem is applicable to your environment and if you should bypass the specific ERROR HOLDS in order to continue the installation of the FMIDs.

This method requires more initial research, but can provide resolution for all HIPERs that have fixing PTFs available and are not in a PE chain. Unresolved PEs or HIPERs might still exist and require the use of BYPASS.

- b. To install the FMIDs without regard for unresolved HIPER APARs, you can add the BYPASS(HOLDCLASS(HIPER)) operand to the APPLY CHECK command. This will allow you to install FMIDs even though one or more unresolved HIPER APARs exist. After the FMIDs are installed, use the SMP/E REPORT ERRSYSMODS command to identify unresolved HIPER APARs and any fixing PTFs.

```
APPLY S(fmid,fmid,...) CHECK
FORFMID(fmid,fmid,...)
SOURCEID(RSU*)
FIXCAT(IBM.ProductInstall-RequiredService)
GROUPEXTEND
BYPASS(HOLDCLASS(HIPER)) .
..any other parameters documented in the program directory
```

This method is quicker, but requires subsequent review of the Exception SYSMOD report produced by the REPORT ERRSYSMODS command to investigate any unresolved HIPERs. If you have received the latest HOLDDATA, you can also choose to use the REPORT MISSINGFIX command and specify Fix Category IBM.ProductInstall-RequiredService to investigate missing recommended service.

If you bypass HOLDS during the installation of the FMIDs because fixing PTFs are not yet available, you can be notified when the fixing PTFs are available by using the APAR Status Tracking (AST) function of ServiceLink or the APAR Tracking function of ResourceLink.

2. After you take actions that are indicated by the APPLY CHECK, remove the CHECK operand and run the job again to perform the APPLY.

Note: The GROUPEXTEND operand indicates that SMP/E applies all requisite SYSMODs. The requisite SYSMODS might be applicable to other functions.

Expected Return Codes and Messages from APPLY CHECK: You will receive a return code of 0 if this job runs correctly.

Expected Return Codes and Messages from APPLY: You will receive a return code of 0 if this job runs correctly.

6.1.15 Perform SMP/E ACCEPT

Edit and submit sample job AKG8ACPT to perform an SMP/E ACCEPT CHECK for Developer for z Systems Host Utilities. Consult the instructions in the sample job for more information.

To receive the full benefit of the SMP/E Causer SYSMOD Summary Report, do *not* bypass the PRE, ID, REQ, and IFREQ on the ACCEPT CHECK. The SMP/E root cause analysis identifies the cause of *errors* but not *warnings* (SMP/E treats bypassed PRE, ID, REQ, and IFREQ conditions as warnings rather than errors).

Before you use SMP/E to load new distribution libraries, it is recommended that you set the ACCJCLIN indicator in the distribution zone. In this way, you can save the entries that are produced from JCLIN in the distribution zone whenever a SYSMOD that contains inline JCLIN is accepted. For more information about the ACCJCLIN indicator, see the description of inline JCLIN in the SMP/E Commands book for details.

After you take actions that are indicated by the ACCEPT CHECK, remove the CHECK operand and run the job again to perform the ACCEPT.

Note: The GROUPEXTEND operand indicates that SMP/E accepts all requisite SYSMODs. The requisite SYSMODS might be applicable to other functions.

Expected Return Codes and Messages from ACCEPT CHECK: You will receive a return code of 0 if this job runs correctly.

If PTFs that contain replacement modules are accepted, SMP/E ACCEPT processing will link-edit or bind the modules into the distribution libraries. During this processing, the Linkage Editor or Binder might issue messages that indicate unresolved external references, which will result in a return code of 4 during the ACCEPT phase. You can ignore these messages, because the distribution libraries are not executable and the unresolved external references do not affect the executable system libraries.

Expected Return Codes and Messages from ACCEPT: You will receive a return code of 0 if this job runs correctly.

6.1.16 Run REPORT CROSSZONE

The SMP/E REPORT CROSSZONE command identifies requisites for products that are installed in separate zones. This command also creates APPLY and ACCEPT commands in the SMPPUNCH data set. You can use the APPLY and ACCEPT commands to install those cross-zone requisites that the SMP/E REPORT CROSSZONE command identifies.

After you install Developer for z Systems Host Utilities, it is recommended that you run REPORT CROSSZONE against the new or updated target and distribution zones. REPORT CROSSZONE requires

a global zone with ZONEINDEX entries that describe all the target and distribution libraries to be reported on.

For more information about REPORT CROSSZONE, see the SMP/E manuals.

6.1.17 Cleaning Up Obsolete Data Sets, Paths, and DDDEFs

The web download data sets listed in Figure 13 on page 14 (section 5.2.3, “DASD Storage Requirements” on page 12) are temporary data sets. You can delete these data sets after you complete the SMP/E install.

The following file system paths, which were created and used by previous releases of this product, are no longer used in this release. You can delete these obsolete file system paths after you delete the previous release from your system.

- /usr/lpp/rdzutil/

6.2 Activating Developer for z Systems Host Utilities

6.2.1 File System Execution

If you mount the file system in which you have installed Developer for z Systems Host Utilities in read-only mode during execution, then you do not have to take further actions to activate Developer for z Systems Host Utilities.

6.3 Product Customization

The publication *IBM Developer for z Systems Host Configuration Guide (SC27-8577)* contains the necessary information to customize and use Developer for z Systems Host Utilities.

6.4 Product FMIDs

The product in which you received Developer for z Systems Host Utilities contains multiple FMIDs, some of which provide services utilized by Developer for z Systems Host Utilities.

- IBM Developer for z Systems
IBM Developer for z Systems provides development related services. Installation information can be found in *Program Directory for IBM Developer for z Systems (G111-8298)*.
- IBM Developer for z Systems Host Utilities
IBM Developer for z Systems Host Utilities provides batch code analysis related services. Installation information can be found in *Program Directory for IBM Developer for z Systems Host Utilities (G113-2864)*.

- IBM z/OS Debugger
IBM z/OS Debugger provides debug related services. Installation information can be found in *Program Directory for IBM z/OS Debugger* (GI13-4540).

Some functions in Developer for z Systems Host Utilities require services provided by IBM z/OS Debugger.
- IBM COBOL and CICS Command Level Conversion Aid for OS/390 and MVS and
IBM COBOL and CICS Command Level Conversion Aid for OS/390 and MVS and provides services to handle older COBOL programs. Installation information can be found in *Program Directory for IBM COBOL and CICS Command Level Conversion Aid for OS/390 and MVS and* (GI10-5080).
- IBM Application Delivery Foundation for z Systems Common Components
IBM Application Delivery Foundation for z Systems Common Components provides services shared by multiple products. Installation information can be found in *Program Directory for IBM Application Delivery Foundation for z Systems Common Components* (GI10-8969).
- IBM Explorer for z/OS
IBM Explorer for z/OS provides z/OS access related services shared by multiple products. Installation information can be found in *Program Directory for IBM Explorer for z/OS* (GI13-4314).

7.0 Notices

This information was developed for products and services offered in the U.S.A. IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

APAR numbers are provided in this document to assist in locating PTFs that may be required. Ongoing problem reporting may result in additional APARs being created. Therefore, the APAR lists in this document may not be complete. To obtain current service recommendations and to identify current product service requirements, always contact the IBM Customer Support Center or use S/390 SoftwareXcel to obtain the current "PSP Bucket".

IBM may have patents or pending patent applications covering subject matter in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to the

IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk, New York 10504-1785
USA

For license inquiries regarding double-byte (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

Intellectual Property Licensing
Legal and Intellectual Property Law
IBM Japan, Ltd.
19-21, Nihonbashi-Hakozakicho, Chuo-ku
Tokyo 103-8510, Japan

7.1 Trademarks

IBM, the IBM logo, and ibm.com are trademarks or registered trademarks of International Business Machines Corp., registered in many jurisdictions worldwide. Other product and service names might be trademarks of IBM or other companies. A current list of IBM trademarks is available on the Web at "Copyright and trademark information" at www.ibm.com/legal/copytrade.shtml.

Reader's Comments

Program Directory for IBM Developer for z Systems Host Utilities, September 2017

We appreciate your input on this publication. Feel free to comment on the clarity, accuracy, and completeness of the information or give us any other feedback that you might have.

Use one of the following methods to send us your comments:

1. Send an email to comments@us.ibm.com
2. Use the form on the Web at:

www.ibm.com/software/data/rcf/

When you send information to IBM, you grant IBM a nonexclusive right to use or distribute the information in any way it believes appropriate without incurring any obligation to you.

IBM or any other organizations will only use the personal information that you supply to contact you about the issues that you submit.

Thank you for your participation.



Printed in USA

G113-2864-08

